



Model: RAM-3318-LCD

### Description

The RAM-3318-LCD Remote Annunciator is used as a component of an FX-3318 Fire Alarm System. It provides an exact mimic of the FX-3318 display at a remote location.

The display is four lines, 20 characters back-lit alphanumeric LCD. It displays information regarding the panel, its circuits, and devices. An on-screen cursor is controlled by the cursor buttons for menu selection and control.

### Features

- 4 line, 20 character back-lit alphanumeric LCD display.
- Common feature LEDs and push buttons.
- Alphanumeric keypad for the LCD.
- Each RAM-3318-LCD has its own address. Addresses available are 1 to 7 inclusive.
- Cursor buttons for menu selection and control.
- Mounted using one of the BB-1000 or series semi-flush enclosures.

### Electrical Ratings

<b>Power Limited Nominal Voltage:</b>	
	24 VDC
<b>Current Consumption:</b>	
Standby:	70 mA
Alarm:	100 mA
<b>All LEDs illuminated:</b>	
	40 mA Max.

### Ordering Information

Model	Description
RAM-3318-LCD	Remote LCD Annunciator

