

Fire Fighter Telephones



Description

Secutron's Fire Fighter Telephones are designed to operate in conjunction with Secutron's MMX Intelligent Fire Alarm & Network System. These telephone handsets are permanently installed throughout a building to allow Fire Fighters easy communication with the main control panel. The Fire Fighter telephone stations provide a handset behind a locked door. Equipped with a "break glass" feature, the unit can be accessed by unlocking the door or breaking the glass section. The breakable glass section clearly indicates "To open use key or break glass" in order to access the unit.

In addition to the Fire Fighter telephone stations, Secutron provides portable Fire Fighter telephone handsets which plug-in to permanently installed telephone jacks throughout the building. Plugging in the portable handset allows the Fire Fighters to communicate with the main control panel. As with the permanently installed telephones, these portable handsets are made from durable ABS plastic and come equipped with a coiled cord and a male phone plug which plugs into the Fire Fighters' telephone jack. In addition, an optional handset storage cabinet is available to store up to six portable handsets. An optional flush trim ring is available for the storage cabinet.

Features

- Heavy-duty construction
- Red finish
- Flush or surface mount
- Key-locked door
- Break glass insert
- Rugged ABS plastic handset with coiled cord
- Portable handsets and telephone jacks (optional)
- Optional storage cabinet for portable handsets
- Supervised wiring

Operation

The Fire Fighter Telephone handset rests on a cradle inside the enclosure. Lifting the remote handset from the cradle causes a buzzer to sound and lights a "Common Call" indicator or a zone indicator, if provided, at the Emergency Voice Evacuation panel, while the caller hears a steady tone indicating that a call is being made.

The portable handsets plug-in to the Fire Fighters' telephone jacks which are located throughout the building. Plugging in a portable telephone handset causes a buzzer to sound and lights a "Common Call" indicator or a zone indicator, if provided, at the Emergency Voice Evacuation panel, while the caller hears a steady tone indicating that a call is being made.

Engineer Specifications

The remote telephone stations shall consist of a model FT-300 Telephone Chassis Assembly complete with a BB-330 backbox and MMX-TC-330U Flush Mount Enclosure Cover with lock and break glass insert or a MMX-TC-331U Surface Mount Enclosure Cover with lock and break glass insert. The telephone unit shall be made of red ABS plastic and be equipped with a coiled cord. The backbox and enclosure cover shall be finished in red enamel. The door shall bear a handset symbol and breakable glass with words "FIRE FIGHTER'S TELEPHONE", "TO OPEN, USE KEY OR BREAK GLASS". Lifting the handset shall automatically identify and announce a call at the Emergency Voice Evacuation panel. A ring signal tone shall be heard in the handset until the call has been answered.



S5434



FT-300A Telephone Chassis Assembly

The FT-300A consists of the red telephone handset with coiled cord and red enclosure plate.



BB-330 Backbox for Fire Fighters' Handset

Red finish backbox for flush or surface mounting.

Backbox Dimensions:
14"H x 7"W x 3.5"D



Fire Fighters' Handset Enclosure Covers

Red finish covers complete with break glass, lock and keys. Available as Surface cover and Flush mount cover.

MMX-TC-330U Flush Enclosure Cover
Dimensions: 15"H x 8"W

MMX-TC-331U Surface Enclosure
Cover Dimensions: 14.2"H x 7.2"W



Fire Fighters' Portable Handset & Fire Fighters' Telephone Jack

The red portable telephone handset comes with a coiled cord and a male phone plug which plugs into the Fire Fighters' Telephone Jack, allowing Fire Fighters to make direct communication with the main control panel. The Fire Fighters' Telephone Jack consists of a single phone jack which is mounted on a single gang, plastic plate. The plastic plate is marked "FIRE FIGHTERS' TELEPHONE" and mounts to any standard single gang box.



FHC-300 Fire Phone Storage Cabinet

The FHC-300 Storage Cabinet holds up to six portable FH-100A telephone handsets. The FHC-300 is a surface mount enclosure and comes with a keylocked door.

Dimensions:
13.50"H x 21.25"W x 3.75"D

Ordering Information

Model	Description
FT-300A	Telephone Chassis Assembly c/w Handset and coiled cord
BB-330	Backbox for Fire Fighters' Handset
MMX-TC-330U	Flush Mount Enclosure Cover c/w with lock and break glass insert
MMX-TC-331U	Surface Mount Enclosure Cover c/w lock and break glass insert
FH-100A	Portable Fire Fighters' Telephone Handset
MMX-FJ-100P	Remote fire Fighter's Telephone Jack, Plastic Plate
FHC-300	Emergency Telephone Handsets Storage Cabinet (Holds up to six portable handsets.)
TR-300	Flush Trim Ring for FHC-300

THIS INFORMATION IS FOR MARKETING PURPOSES ONLY AND NOT INTENDED TO DESCRIBE THE PRODUCTS TECHNICALLY.

For complete and accurate technical information relating to performance, installation, testing and certification, refer to technical literature. This document contains intellectual property of Mircom. The information is subject to change by Mircom without notice. Mircom does not represent or warrant correctness or completeness.

SECURON Catalog Number

1016
Issue 4
Page 2 of 2